

littleBits™ education

STEAM STUDENT SET INVENTION GUIDE

↓
**DOWNLOAD THE
TEACHER'S GUIDE**
and other classroom
resources at
littleBits.cc/student-set



littleBits™ education
**STEAM
 STUDENT SET
 INVENTION GUIDE**



- 04 littleBits Basics
- 06–27 **BIT™ INDEX**
- 07 **POWER**
- 09 **INPUT**
- 14 **WIRE**
- 17 **OUTPUT**
- 24 **ACCESSORIES**
- 28 Inventing with littleBits

- 32–58 GUIDED CHALLENGES**
- Guided challenges start with instructions for a simple invention. Once you've created the invention, the challenge moves into the Remix phase where creativity really takes off.
- 32 Invent a Self-Driving Vehicle
 - 39 Invent an Art Machine
 - 46 Invent a Throwing Arm
 - 53 Invent a Security Device

- 59–70 OPEN CHALLENGES**
- Open challenges get you to flex your creative muscles. These challenges start with an open-ended problem. Your mission is to explore ways you could use littleBits to create an invention that solves that problem.
- 59 Hack Your Classroom
 - 62 Invent for Good
 - 65 Invent a Chain Reaction Contraption
 - 68 Hack Your Habits

- 71 Troubleshooting Tips
- 72 Continue Your Inventor Journey

STEAM is the evolution of **STEM** education, adding *Art* to Science, Technology, Engineering, and Math. Students gain technical skills by exploring creative, collaborative solutions to real-world problems.

The challenges in the littleBits STEAM Student Set link to **NGSS** (Next Generation Science Standards) Engineering Design standards.



TEACHER'S GUIDE and other classroom resources available at littleBits.cc/student-set.



SHARE & DISCOVER inventions on the littleBits Invent App or online at littleBits.cc/invention.




WE IN INVE
WORLD
WANT TO




NOT THE
WE
D LIVE IN.

BUILD & PLAY WITH THIS CIRCUIT FIRST




littleBits™ BASICS



2 COLOR-CODED BY FUNCTION
Bits™ are grouped into four different categories, which are color-coded.

- A POWER (BLUE)**
Power Bits, plus a power supply, run power through your circuit.
- B INPUT (PINK)**
Input Bits accept input from you or the environment and send signals that affect the Bits that follow.
- C WIRE (ORANGE)**
Wire Bits connect to other systems and let you build circuits in new directions.
- D OUTPUT (GREEN)**
Output Bits do something - light up, buzz, move...

Learn more about your Bits in the **BIT INDEX ON PG 06**



3 MAGNET MAGIC!
Bits snap together with magnets. The magnets are always right – you can't snap them together the wrong way.

ARROWS SHOULD POINT IN THE SAME DIRECTION




IF THE BITS WON'T SNAP TOGETHER, TRY SPINNING ONE AROUND AND MAKE SURE THE ARROWS POINT IN THE SAME DIRECTION




4 ORDER IS IMPORTANT
POWER BITS always come first and **INPUT BITS** only affect the **OUTPUT BITS** that come after them.

WITH NO OUTPUT BIT AFTER IT, THE INPUT BIT HAS NOWHERE TO SEND ITS SIGNAL




THE INPUT BIT AFFECTS THE OUTPUT BITS THAT FOLLOW



5 SOME BITS ARE ADJUSTABLE
Switches, buttons, and dials on the board allow you to change how the Bit functions.

FLIP THE SWITCH TO CHANGE MODES

ADJUST SENSITIVITY WITH PURPLE SCREWDRIVER



littleBits™ BIT™ INDEX

POWER

- 07** p1 power
- 08** p3 USB power

INPUT

- 09** i3 button
- 10** i5 slide dimmer
- 11** i12 temperature sensor
- 12** i13 light sensor
- 13** i16 pulse

WIRE

- 14** w1 wire
- 15** w7 fork
- 16** w10 inverter

OUTPUT


- 17** o2 long LED
- 18** o3 RGB LED
- 19** o6 buzzer
- 20** o11 servo
- 21** o13 fan
- 22** o21 number
- 23** o25 DC motor

ACCESSORIES

- 24** a5 magnet shoes
- a6 hook & loop shoes
- a9 mounting board
- 25** a10 motorMate
- a14 USB power adapter
- 26** a19 servo hub
- a23 mechanical arm
- 27** a24 servo mount
- a25 wheel

* Occasionally Bits™ get updated, so the features or appearance of your Bits may differ from those used in this guide.


p1 POWER



MEET THE BIT

Every circuit starts with power. It provides the electricity that makes your Bits spin, buzz, blink, and shine.

SAMPLE CIRCUIT



HOW IT WORKS

The power Bit converts the 9 volts of electricity in the battery to the 5 volts that littleBits circuits run on.


The power Bit also sends a signal through your circuit. Controlling this signal with inputs is how you control your circuit.

REAL WORLD ANALOGIES



PHONE CHARGER

p3 USB POWER



MEET THE BIT


The USB power may be the smallest in the series, but it's big enough to send electricity to all your creations. This Bit lets you power your circuit through a micro USB cable. It can be connected to a computer or wall adapter for non-stop power.

SAMPLE CIRCUIT

o3 RGB LED

p3 USB POWER

 On light



HOW IT WORKS

Like the power Bit, the USB power Bit sends a 5 volt signal through your circuit, which allows you to control your Bits.


Instructions for the projects in this Kit use the p1 power Bit, but you can use the USB power for all of them as well.

REAL WORLD ANALOGIES



PHONE CHARGER


i3 BUTTON



MEET THE BIT

The button Bit is a classic: big, round, and springy for comfortable pressing! Push it to turn something on and release it to turn it off.

SAMPLE CIRCUIT



HOW IT WORKS

The button is like a door. When you press it, the door opens, letting the signal pass through the Bit and on to the next Bits in the circuit. The button is a momentary switch, you must continue to press it for the signal to flow. When you release the button, the door closes, stopping the signal from passing on to other Bits.

MINI-CHALLENGE

Can you invent a chair that makes noise when you sit down?

REAL WORLD ANALOGIES



VIDEO GAME CONTROLLER




ELEVATOR BUTTON



GAME SHOW BUZZER

i5 SLIDE DIMMER




MEET THE BIT

Slide this dimmer back and forth to control your circuit. As you slide it up, more signal goes to the Bits that follow, brightening lights, speeding up motors, and raising the volume on your buzzer.

MINI-CHALLENGE

Can you invent something with the slide dimmer that waves a flag back and forth? How could you change the speed it waves?

SAMPLE CIRCUIT




HOW IT WORKS

When the slider is all the way to the left, it's sending an off or 0 volt signal. When the slider is all the way to the right, it's sending a 5 volt signal. The slider can be positioned to send any signal between 0 and 5 volts.

REAL WORLD ANALOGIES



HOUSEHOLD DIMMER SWITCH




STEREO VOLUME CONTROL



CAR PEDAL


i12 TEMPERATURE SENSOR



MEET THE BIT

With the temperature sensor you can use the temperature in the surrounding air to control your circuit. It's especially useful for gathering data when paired with the number Bit set to **VALUE** mode.

SAMPLE CIRCUIT



HOW IT WORKS

The temperature sensor takes a measurement from the environment and translates it into a signal. The higher the temperature it senses, the more signal it sends out to the following Bits (making lights brighter and motors turn faster).

MINI-CHALLENGE

Can you invent a temperature-controlled gadget to beat the summer heat?

REAL WORLD ANALOGIES



THERMOSTAT




MEDICAL THERMOMETER



AUTOMATIC TEA KETTLE

A temperature sensor tells your automatic kettle when to turn off.

i13 LIGHT SENSOR




MEET THE BIT

Use this Bit to control your circuits with light! The amount of light shining on the sensor will change how your circuit behaves. It's a great way to activate your circuit without hands and is perfect for alarms!




MINI-CHALLENGE

Can you invent something that moves when the lights go out?

SAMPLE CIRCUIT



i13 LIGHT SENSOR

-  **MODE:** light or dark
-  **SENSITIVITY:** "-" decrease, "+" increase
-  This is the component that measures light.

HOW IT WORKS

The light sensor measures how much light is shining on it. It has two modes. In **LIGHT** mode, as the light shining on the sensor gets brighter, more signal passes through it (making lights brighter or motors turn faster). In **DARK** mode, the signal increases as it gets darker.

Use the purple screwdriver to turn the dial and adjust how much light it takes to change the signal. Clockwise increases sensitivity, counter-clockwise decreases it.


REAL WORLD ANALOGIES



NIGHT LIGHT SENSOR




PHOTOGRAPHER'S LIGHT METER



FINGER PULSE METER

A pulse meter shines a bright light into your finger and uses a light sensor to measure blood flow.

i16 PULSE




MEET THE BIT

The pulse is like a heartbeat that makes the Bits after it turn on and off in a steady rhythm.

MINI-CHALLENGE

Can you invent a warning signal with the pulse? How can you make the signal pulse faster or slower?

SAMPLE CIRCUIT



HOW IT WORKS

The pulse is a switch that opens and closes over and over again. When it's open, the signal from the previous Bit passes through to the next Bit. When the switch closes, the signal is blocked.

Use the purple screwdriver to adjust the dial. You can change the speed of the rhythm by turning the small dial on the Bit with your purple screwdriver.

REAL WORLD ANALOGIES



POLICE SIREN



FIREFLY




TURN SIGNAL



CLOCK SECONDHAND

w1 WIRE




MEET THE BIT

The wire Bit has a flexible wire running between its two bitSnaps. This allows you to place your Bits farther apart, turn corners, and make connections that can twist, turn, and spin.

MINI-CHALLENGE

Can you invent a circuit that uses the wire to shine the RGB LED on the light sensor?

SAMPLE CIRCUIT




HOW IT WORKS

The wire doesn't change the signal in any way - it just carries it over from one Bit to another.

REAL WORLD ANALOGIES



EXTENSION CORD




POWER LINES



STRING OF LIGHTS

w7 FORK




MEET THE BIT

The fork gives you more options for connecting your Bits; it lets you connect a single Bit to as many as three others. If you place an input before the fork, it will control all three outputs at once, such as light, sound, and motion.

MINI-CHALLENGE

Can you invent a circuit where an input controls three outputs?

SAMPLE CIRCUIT



HOW IT WORKS

The fork takes the incoming signal and sends it to all three output bitSnaps.

REAL WORLD ANALOGIES




POWER STRIP



FORK IN THE ROAD

w10 INVERTER




MEET THE BIT

The inverter is an example of a logic Bit. It sends out the opposite of whatever it receives: send it an *on* signal, and the inverter changes it to an *off* signal, or vice versa. Would you like a button that turns things *off* instead of *on*? Try the inverter.

MINI-CHALLENGE

Can you invent something with the inverter that alerts you if someone takes a book off the table?

SAMPLE CIRCUIT



HOW IT WORKS

Anytime the inverter receives a signal lower than 50% power (2.5 volts) the inverter sends full power (5 volts) to the next Bit in the circuit. If the inverter receives a signal greater than 2.5 volts, the inverter sends 0 volts to the next Bit in the circuit.

REAL WORLD ANALOGIES




OPPOSITE DAY



ALTERNATING POLICE LIGHTS

Try this: power, pulse, light, inverter, light.

o2 LONG LED




MEET THE BIT

The long LED is a flexible lighting option. We call it the “long” LED because the light is connected to the board by a cable, which lets you put the light in some interesting places.

MINI-CHALLENGE

Can you invent a new wearable accessory using the long LED?

SAMPLE CIRCUIT



HOW IT WORKS

This Bit uses a light-emitting diode (LED) to turn electricity into light. The more signal you send the Bit, the brighter the light shines.

REAL WORLD ANALOGIES



FLASHLIGHT




STREET LAMP



ANGLERFISH

o3 RGB LED



MEET THE BIT




The RGB LED is a light with adjustable color. You can use the purple screwdriver to turn the dials and create your own custom color mix of red, green, and blue.


MINI-CHALLENGE

Can you invent a flashlight that uses your favorite color?

SAMPLE CIRCUIT

o3 RGB LED

-  **R:** Adjust the amount of red light
-  **G:** Adjust the amount of green light
-  **B:** Adjust the amount of blue light



HOW IT WORKS

The RGB LED is actually three very small lights (a red, a blue, and a green light). Turning the dials changes the brightness of each light. The colors from these lights mix together to create every color in the rainbow.

REAL WORLD ANALOGIES



TRAFFIC LIGHT

Thousands of RGB LEDs create these displays




JUMBOTRON



DECORATIVE LIGHTS

o6 BUZZER




MEET THE BIT

The buzzer makes a sound no one can ignore. It's great at sounding the alarm or annoying those nearby.

MINI-CHALLENGE

Can you invent a way to communicate with your friends using the buzzer?


SAMPLE CIRCUIT



HOW IT WORKS

The buzzer converts the electrical signal it receives into a vibration, which creates a buzzing sound. The higher the signal it receives, the more intense the vibration, and the louder the sound is.

REAL WORLD ANALOGIES



DOORBELL




CAR ALARM



WASHING MACHINE

o11 SERVO



MEET THE BIT


The servo is a motor that can swing back and forth or be turned to a specific position.

There are a few accessories you can use with the servo (like the mechanical arm). You can find out how to use those on pages 26 and 27.

MINI-CHALLENGE

Can you invent something that uses the servo to clean up your desk?

SAMPLE CIRCUIT



HOW IT WORKS


The servo has two modes. In **TURN** mode, the input from other Bits determines the position of the hub - try using a dimmer to set the angle you want. In **SWING** mode, the servo will move back and forth on its own like a pair of windshield wipers - the input signal controls the speed of the swing.

The servo's range of motion is about 110 degrees.


REAL WORLD ANALOGIES



TRUCK CRANE




WINDSHIELD WIPERS



ROBOT

o13 FAN




MEET THE BIT

Use the fan to create a gentle breeze, perfect for cooling things off. You can also try taping small things (like stickers or pieces of paper) to the center of the fan for some spinning visuals.

MINI-CHALLENGE

Can you invent something that uses the fan to move an object across the table?

SAMPLE CIRCUIT



HOW IT WORKS

Inside the fan is a tiny motor. When it receives a signal, it spins. The more signal it receives, the faster it spins.

REAL WORLD ANALOGIES



LEAF BLOWER




PERSONAL FAN



AIRPLANE PROPELLER

o21 NUMBER




MEET THE BIT

The number displays information that it receives from the Bits before it. It's a great way to measure the input from sensors or count things, like the score in a game.

MINI-CHALLENGE

Can you invent a game that uses an automatic score counter?

SAMPLE CIRCUIT



HOW IT WORKS

The number Bit displays information about the signal it's receiving.

In **COUNT** mode, the Bit can count up or down when the Bit receives an input signal over 2.5 volts. It can be reset by receiving a signal through the reset bitSnap.

In **READ** mode, the Bit displays information about the signal it's receiving in either volts ranging from 0.0–5.0 or values ranging from 0–99.

The signal leaving the Bit will always match the number being displayed, even in **COUNT** mode. For example, if you count up to 38, the signal leaving the Bit will be 38% of full power.

REAL WORLD ANALOGIES



SCOREBOARD




VOLUME INDICATOR ON TV



SPEEDOMETER

o25 DC MOTOR



MEET THE BIT


Use the motor to spin, turn, twist, and roll.

There are a few accessories you can use with the DC motor (like wheels). You can find out how to use those on pages 25 - 27.

MINI-CHALLENGE

Can you invent something using the DC motor that travels across the table?

SAMPLE CIRCUIT



o25 DC MOTOR



MODE: CW (clockwise), VAR (variable mode), and CCW (counterclockwise)



Can be mounted to other materials with included #6 screws.



Feet for attaching to mounting boards or shoes

HOW IT WORKS

The DC (or "direct current") motor rotates a shaft when it receives a signal. The more signal it receives, the faster the motor will spin.

A switch on the board lets you choose which direction the motor spins. **CW** spins clockwise and **CCW** spins counterclockwise. When the switch is in **VAR** (variable) mode, the amount of signal the motor receives from previous Bits allows you to control the speed and direction (clockwise or counterclockwise) of its motion. In this mode, using an input like a slide dimmer makes steering easy!

REAL WORLD ANALOGIES



CAR ENGINE




DRILL



FERRIS WHEEL

a5 MAGNET SHOES

a6 HOOK & LOOP SHOES



MEET THE ACCESSORY

Shoes slip onto your Bits' feet and hold your circuit together. On the bottom of your shoes you'll find magnets or hook & loops, which are great for securing your circuits to different surfaces.


HOW IT WORKS

First, snap together your littleBits circuit. Then press the feet of your Bits into the holes of the shoes and place it on your chosen surface.


Magnet shoes allow you to adhere your circuit to any magnetic surface. Try your refrigerator or your locker!

Hook & loop shoes come with an adhesive-backed hook & loop strip. The strip can be cut to any size you desire and affixed to clothing, fabric, or any flexible surface.

bitFeet™ go in the shoes



a9 MOUNTING BOARD



MEET THE ACCESSORY

The mounting board is like the backbone of some of your inventions. It allows you to keep your circuit intact and move it around with ease! It also provides structure which is helpful for building out projects, like a vehicle.


HOW IT WORKS

Snap together your littleBits circuit and press the feet of your Bits into the holes of the mounting board.

NOTE: Your circuit must be complete before you press it onto the board. You won't be able to add Bits one at a time.



PRESS DOWN ON BITSNAPS NOT WHITE CIRCUIT BOARD.



Use the included #6 screws in each of the corner holes to permanently attach to any surface.

a10 MOTORMATE




MEET THE ACCESSORY

The motorMate makes it easy to attach paper, cardboard, LEGO® axles, and lots of other materials to the DC motor.

HOW IT WORKS


To mount, slide the motorMate onto the shaft of the DC motor by aligning the flat edges. The motorMate has two different sized slots: one fits most standard craft sticks and the other fits thicker papers like cardstock. LEGO axles fit right into the center.



a14 USB POWER ADAPTER & CABLE

MEET THE ACCESSORY

This power adapter and USB cable combo is the perfect way to provide long-term power to your littleBits creations.




HOW IT WORKS

This power adapter converts your 120 volt wall power into the 5 volt power that littleBits circuits run on. Simply connect the cable to your littleBits USB power Bit (this only connects to the p3 USB power Bit). You can also use the USB cable to power your circuits from a computer or rechargeable USB battery.

NOTE: Input: 100-240V AC 50/60Hz; Output: 5.0V DC 2000mA. Included adapter is for US electrical outlets only.

a19 SERVO HUB




MEET THE ACCESSORY

The servo hub lets you easily attach materials to your servo motor and add more complex movements to your littleBits inventions.

HOW IT WORKS

The servo hub can be attached and removed by gently pushing or pulling it on or off the servo motor. This is helpful if you need to reorient how the holes are positioned for a project.

a23 MECHANICAL ARM



MEET THE ACCESSORY


The mechanical arm attaches to both the servo hub and the DC motor shaft, and offers lots of leverage for pushing, pulling, and throwing.

HOW IT WORKS


To attach the mechanical arm to the servo hub, use two of the #6 screws (included) and a Phillips head screwdriver (not the purple screwdriver). Be sure to screw through the holes on the servo hub.

To attach the mechanical arm to the DC motor, line up the flat edge of the DC motor shaft with the flat edge of either of the flat-edged holes on the mechanical arm.

The two large holes on the end are perfect for holding pens and markers in place.




a24 SERVO MOUNT




MEET THE ACCESSORY

The servo mount lets you attach your servo to a mounting board or a pair of littleBits shoes. It's a great way to keep the servo steady so the arm can go wild.




Connect to servo hub with included #6 screws



USE A PHILLIPS HEAD SCREWDRIVER


Feet for mounting boards and shoes

a25 WHEEL




MEET THE ACCESSORY

When used with a DC motor, this wheel is perfect for making bots, cars, and all sorts of spinning inventions.



HOW IT WORKS

The metal shaft of the DC motor and the hole in the wheel are both flat edged. To attach the wheel to the DC motor shaft, align the flat edge of the hole in the wheel with the flat edge of the motor shaft. Press firmly to slide it on.



The wheel also connects to the servo hub using the included #6 screws.


THE LITTLEBITS™ INVENTION CYCLE

What is the Invention Cycle?
The Invention Cycle is a roadmap for your invention journey. Each phase is full of activities and questions that help you explore your ideas and develop your invention.

DO I HAVE TO GO THROUGH THE INVENTION CYCLE EXACTLY IN ORDER?

Nope! If you want, you can remix while you play or share while you create. Each phase of the invention cycle represents a different way of thinking and making. They work well in order, but a good design process is always a bit messy.





CREATE

PUT SOMETHING TOGETHER. You can build it from the instructions or make something from your imagination. Don't worry if it doesn't work or if it isn't perfect. The important thing is to create your first model so you have something to experiment with.

PLAY!

USE IT! Playing with what you've created is fun, but also an important part of inventing. Playing is like a test run. It's a chance to see how well your invention works and look for ways you can make it better.

REMIX

IMPROVE YOUR INVENTION. Keep experimenting! Add new Bits, swap parts with other inventions, or take all the pieces apart and put them together in a different way.

SHARE

INSPIRE OTHERS. Show the world what you've created. Get inspired by exploring what others have shared. Create, play with, and remix other inventions. This is how awesome new inventions are born.



TURN DIAL CLOCKWISE (CW):
Use the purple screwdriver to turn the dial on the Bit all the way clockwise.



TURN DIAL COUNTER-CLOCKWISE (CCW):
Use the purple screwdriver to turn the dial on the Bit all the way counterclockwise.



CHANGE MODE
Some Bits have a switch that changes how the Bit works. This icon will tell you which mode your switch should be in.

ICON INDEX



POWER ON/OFF:
The p1 power Bit™ has an on/off switch. This icon will let you know when it's time to turn it on or off.



PRO TIPS
Keep your eyes open for these bits of littleBits wisdom. These tips will help build your invention skills and level up your inventions.



USE RUBBER BAND OR MASKING TAPE
This icon will tell you when to use rubber bands or some masking tape to keep something in place.



TEST YOUR CIRCUIT
Before you play with your new invention, you'll turn the power on and make sure all your Bits™ are doing their jobs.



EXTRA IMPORTANT INFO!
This icon will let you know when there is a small, but very important step we don't want you to miss. If you ignore these your invention won't work.




PHILLIPS HEAD
The metal screws included with your set require a Phillips head screwdriver (not included). Do not use the plastic purple screwdriver on these screws.



USE THE LITTLEBITS APP
Discover inventions, connect with the littleBits community, and easily upload and share your own creations.

PROTOTYPING TIPS

WHAT'S A PROTOTYPE, YOU ASK? A prototype is a model that helps you test an idea. This is the first step in turning your ideas into actual inventions. Building a prototype helps you learn what you like, what works, and what needs more figuring out. You'll be building a lot of prototypes during the challenges in this booklet.



DON'T WORRY ABOUT PERFECTION

or if your invention will work right away – just start making. Do you think the light bulb was invented on the first try? Most inventions take many tries to get right.



BUILD MANY DIFFERENT VERSIONS.

The more you experiment, the more you will learn, and the better your invention will be.



TRY SOME WEIRD AND UNEXPECTED STUFF. You might be surprised at what you discover when you add random materials, flip your prototype upside down, or try using it for a totally different purpose.



DOCUMENT EACH STEP. As your prototype changes, take photos, draw sketches, and jot down notes. The journey from idea to invention is just as exciting and important as the final result. You did a lot of work to bring it to life. Show it proudly!



HELPFUL TOOLS & MATERIALS

THE WORLD AROUND YOU IS FULL OF MATERIALS FOR PROTOTYPING AND CREATING INVENTIONS. At littleBits, we dig through our recycling bins all the time to collect stuff for our projects. In fact, the very first prototype of a Bit was made with cardboard, copper tape, and a few electronic components like LEDs. Here's some of our favorite stuff to work with:



paper or plastic cups



scissors



Phillips head screwdriver




craft sticks



string




sketchbook



construction toys



rubber bands



milk carton



pipe cleaners




markers




duct tape



cereal box



ruler




cardboard tubes



cardboard



plastic bottle




paper

CHALLENGE 01

INVENT A SELF-DRIVING VEHICLE

30
MINUTES
(MINIMUM)

TIME



LEVEL


START BY BUILDING THE CIRCUIT CRUISER, A VEHICLE THAT GETS AROUND ON TWO DC MOTORS. Add extra features to this lean, mean, mobile machine. Use it to deliver school supplies to your friends, help your teacher pass out papers, or wake up your sleeping classmate.




BITS™ + MATERIALS




a1 battery & cable




p1 power



o25 DC motor (×2)




w1 wire



i5 slide dimmer



o25 wheel (×2)




a9 mounting board

• rubber band/tape
(not included)


CREATE

1 BUILD YOUR CIRCUIT.




2

PRESS THE WHEELS ONTO THE DC MOTORS.




3

PRESS YOUR CIRCUIT ONTO THE MOUNTING BOARD.



4


ATTACH THE BATTERY TO THE MOUNTING BOARD NEXT TO THE SLIDE DIMMER.



USE A RUBBER BAND
OR MASKING TAPE TO
ATTACH THE BATTERY.


5

PRESS THE MOTORS ONTO THE MOUNTING BOARD.




6

SET THE FIRST DC MOTOR TO CCW (COUNTERCLOCKWISE) AND THE SECOND DC MOTOR TO CW (CLOCKWISE).



7

TEST YOUR CIRCUIT. With the slide dimmer set all the way up, the car should move forward. Troubleshooting pg 71.



Let's give these wheels a spin!

HOW IT WORKS

o25 DC MOTOR



Control the direction your car drives by flipping the mode switches. Because the motors face opposite directions, they need to be set in opposite spin modes to drive in one direction. Setting the motors to the same direction mode will create a car that spins around in circles.

i5 SLIDE DIMMER

The slide dimmer is like the gas pedal for your car. As you slide it up, more power goes to your motors.


p1 POWER sends a signal through the circuit.

The **w1 WIRE** receives the signal from the power and sends it along to the slide dimmer.

The **i5 SLIDE DIMMER** controls how much power goes to the motors.

The first **o25 DC MOTOR** uses the signal from the slide dimmer to determine its speed. It then passes this signal onto the second motor.

The second **o25 DC MOTOR** reads the signal from the first motor and also uses it to determine its speed.






w1 WIRE

The wire gives you more flexibility in how you position your Bits on the board.

REMIX

HOW CAN YOU LEVEL-UP YOUR CAR? LET'S EXPERIMENT!

SHARE



A CHANGE HOW YOU CONTROL THE CAR.

- Use inputs other than the slide dimmer. Try a light sensor you control with a flashlight, or string two wires together with a button to have a "remote" control.

B SUPE IT UP!

- Add a siren using lights or the buzzer, or a speedometer using the number Bit™.
- Give your vehicle a body or form. Give it some character!
- Use LEGO® to build a bigger car or even a train.


C BUILD A TRAILER FOR YOUR VEHICLE USING MATERIALS AROUND YOU.

- How much stuff can your vehicle haul?

HOST A CAR SHOW! Present the best features of the car you made. Let others test drive it.

ASK YOUR FRIENDS WHAT THEY WOULD USE YOUR VEHICLE FOR – sending messages, passing snacks, borrowing pencils – and show them how it could accomplish that function.






CHALLENGE 02

INVENT AN ART MACHINE

30
MINUTES
(MINIMUM)


TIME




LEVEL

START BY CREATING A DOODLE WIZARD – a bot made with DC motors, and a pulse that dances, wiggles, and draws up a storm. Add your own artistic flair by changing up some of the Bits and materials to create unique masterpieces.


BITS™ + MATERIALS




a1 battery & cable




p1 power




o25 DC motor (×2)



i16 pulse



a25 wheel (×2)




a9 mounting board



a4 screwdriver


- markers
- drawing surface
- rubber band/
masking tape

(not included)




2

ATTACH THE WHEELS TO THE DC MOTORS.




3

PRESS YOUR CIRCUIT ONTO THE MOUNTING BOARD.




4


ATTACH BATTERY TO THE MOUNTING BOARD.




5 ATTACH MOTORS TO THE MOUNTING BOARD.



7 SET THE PULSE SPEED TO THE LOWEST SETTING.




6 ADJUST MOTOR MODES.




8

ATTACH THE MARKER.



9

TEST YOUR CIRCUIT. When you turn the power on, one wheel should spin all the time while the other one alternates between spinning and stopping. Troubleshooting pg 71.



 **PLAY!**

Now let's make some art!
 Make a series of drawings,
 and pick a few of
 your favorites.

HOW IT WORKS

i16 PULSE



The speed dial controls how fast the pulse flips on and off. Adjusting it will change how often and how long the second motor spins.

p1 POWER sends a signal through the circuit.

The first **o25 DC MOTOR** receives that signal and spins at full speed in one direction.

The signal passes through the motor and on to the **i16 PULSE**. The pulse only lets the signal through in short bursts.

When the second **o25 DC MOTOR** gets a signal from the pulse, it spins, but when the pulse switches off, the motor stops.

o25 DC MOTOR






This switch controls which direction the motor spins. Changing the direction of the spin will change how the Doodle Wizard moves.

o25 WHEEL

Your Doodle Wizard's movement is caused by friction between the wheels and the drawing surface. The motion of your Doodle Wizard will change if it is placed on different types of drawing surfaces (e.g. rough paper, glossy paper, or a whiteboard). You could also experiment with adding different materials to the face of the wheels and see how changes in friction change your drawings.

REMIX

WHAT ELSE CAN YOUR INVENTION DO? LET'S EXPERIMENT!



A ADJUST THE BITS TO CREATE YOUR OWN UNIQUE DRAWING STYLE.

- How does changing the speed of the pulse or the direction that the motors spin make your drawings different?
- Which adjustments make your favorite drawings?

B WHAT OTHER MATERIALS CAN YOU USE?

- Use different drawing tools, like chalk, crayons, pens, or pencils.
- Attach multiple drawing tools to use at once.
- Try the Doodle Wizard on different drawing surfaces.

C TRY ADDING NEW BITS.

- What happens when you use a servo to draw?
- What happens when you add or swap an input?

SHARE



SET UP A GALLERY SHOW. Present your art alongside your Doodle Wizard.

SEE IF YOUR AUDIENCE CAN GUESS WHICH BITS YOU USED, JUST BY LOOKING AT YOUR DRAWINGS. Challenge them to invent a machine to recreate your masterpiece.



CHALLENGE 03

INVENT A THROWING ARM

START BY BUILDING A LAUNCHER THAT FLINGS PROJECTILES WITH A SERVO AT THE PRESS OF A BUTTON.

Set up a tower of cups and try to knock them over. Then modify your launcher to make it even more accurate, powerful, or speedy. Challenge your friends to see who can knock over the most cups.

1
HOUR
(MINIMUM)

○
○
○
○
●

TIME


LEVEL




BITS™ + MATERIALS




a1 battery & cable




p1 power




i3 button



o11 servo & servo hub




a24 servo mount



a23 mechanical arm




screws (×3)



a9 mounting board


- Phillips head screwdriver
- scissors
- rubber band
- paper cups
- masking tape

(not included)




CREATE

BUILD YOUR CIRCUIT.




2

PRESS SERVO INTO THE SERVO MOUNT AND SCREW IN.




4

PRESS THE SERVO MOUNT ONTO THE MOUNTING BOARD AND ADJUST SERVO MODE.




3

PRESS YOUR CIRCUIT ONTO THE MOUNTING BOARD.




5

TURN POWER ON.




6

WITH POWER ON, CONNECT THE MECHANICAL ARM TO THE SERVO HUB AT A 90 DEGREE ANGLE TO THE MOUNTING BOARD, AS SHOWN.




7

MAKE A BUCKET FOR THE LAUNCHER.




8

TAPE THE BUCKET TO THE FREE END OF THE MECHANICAL ARM.




9

CRUMPLE UP A HALF SHEET OF NOTEBOOK PAPER TO LAUNCH.



10

TEST YOUR CIRCUIT. Pressing the button should rotate the mechanical arm. Troubleshooting pg 71.




TEST YOUR CIRCUIT.

 **PLAY!**



Now it's game time!
Create a target and invent
a game with your friends.

HOW IT WORKS



p1 POWER sends a signal to the button.

When pressed, the **i3 BUTTON** lets the signal through to the servo.

When the **o11 SERVO** gets the signal, it turns, rotating the arm and throwing the projectile.

a23 MECHANICAL ARM

The farther you place your cup from the servo hub, the faster it will swing. You can experiment with extending the mechanical arm with other materials, but you'll have to pay attention to weight.

As the cup gets farther from the hub, it also takes more force to move it. If your arm gets too long it will overpower the servo motor and will be hard to move. This relationship between distance and force is called torque.




o11 SERVO



When it's in **TURN** mode, the position of the servo is determined by the incoming signal. At 0 volts, the servo is all the way to the left. If the incoming signal is at full power (5 volts), the servo arm is all the way to the right. When the button makes the signal go from 0 to 5 volts quickly, the arm swings quickly. This speed helps your ball fly farther.

REMIX

WHAT DO YOU WANT TO IMPROVE OR CHANGE? LET'S EXPERIMENT!



A TRY EXPERIMENTING WITH THE MECHANICS OF YOUR CATAPULT.

- How does changing the length of the mechanical arm change the throwing distance?
- Try different objects for balls. What gets thrown the farthest? How does the size and shape affect the distance traveled?
- What happens when you change the bucket size or shape? How does it affect the throw?

B HOW COULD USING OTHER BITS MAKE IT BETTER?

- Switch the button with a pulse Bit for automatic firing.
- Add a number Bit to count the number of shots taken.
- Creating a moving target with one of the motors and the other mechanical arm.

C WHAT OTHER GAMES CAN YOU PLAY? COULD YOU INVENT YOUR OWN?

- Try miniature golf, baseball, or bowling!

SHARE



WHAT NEW GAME DID YOU INVENT? Make it official. Give it a name. Write the official rules and share what you created.

GATHER YOUR FRIENDS AND START A TOURNAMENT. What do they think of the game? Is it too easy? Too hard? Just right?






CHALLENGE 04

INVENT A SECURITY DEVICE




TIME




LEVEL

START BY MAKING THE BACKPACK ALARM WITH THE LIGHT SENSOR, PULSE, AND BUZZER. This light-sensitive alarm will alert you if someone is snooping around your stuff. Customize your alarm for different places around the school.


BITS™ + MATERIALS




a1 battery & cable




p1 power



i13 light sensor




i16 pulse



a6 buzzer



a4 purple screwdriver




a6 hook & loop shoes




hook & loop adhesive strip

•backpack
(not included)




2

SET THE MODE AND SENSITIVITY OF THE LIGHT SENSOR.




3

SET THE PULSE SPEED TO THE SLOWEST SETTING.




4

PRESS HOOK & LOOP SHOES ONTO YOUR CIRCUIT.



5


PLACE THE ALARM INSIDE YOUR BACKPACK.



PRO TIP:
TRY USING THE
HOOK & LOOP
STRIP TO KEEP YOUR
CIRCUIT IN PLACE.

6

TEST YOUR CIRCUIT. The buzzer should BUZZ when your circuit is exposed to light, and stop buzzing when it is completely covered up. You may need to adjust the sensitivity of your light sensor to get it just right. Troubleshooting pg 71.



TEST YOUR
CIRCUIT.

 **PLAY!**




Can anyone open your backpack without setting off the alarm?

HOW IT WORKS

i13 LIGHT SENSOR

- Some bags might not be totally dark inside. If your alarm sounds even in the bag, try turning the sensitivity dial down (counterclockwise) a little. If your alarm doesn't sound at all, make sure the sensitivity dial is turned all the way up.
- This is the light sensor component. It only senses light that reaches it, so the direction that the circuit faces will affect how much light is sensed.



i16 PULSE

- The speed adjustment knob will let you adjust how fast (and frantic) your alarm sounds.
- If your pulse Bit is set too fast your buzzer may not have time to vibrate and may not make any noise.

The **p1 POWER** sends a signal through the circuit.



The **i13 LIGHT SENSOR** is in light mode. When the alarm is inside your bag, no light hits the sensor, so it doesn't allow a signal to pass through. When you open the bag, light shines in on the sensor, letting the signal through to the pulse. The more light that shines on the sensor, the more signal it lets through and the louder your buzzer will sound.

The **i16 PULSE** Bit is continuously switching on and off. When it gets a signal from the light sensor, it only lets it through in short bursts.

The **o6 BUZZER** sounds when it gets the signal from the pulse, but is quiet when the pulse flips off. This changing between on and off produces the alarm noise to scare off the snooper.

REMIX

HOW CAN YOU CUSTOMIZE YOUR ALARM?



A CHANGE THE BIT SETTINGS.

- Switch the light sensor mode to **DARK** to create an alarm that sounds when it is dark. Where could an alarm like this be useful?
- If your alarm didn't sound reliably, try adjusting the sensitivity of the light sensor.
- Adjust the speed of the pulse Bit to change how fast the alarm sounds. What setting do you think makes the best alarm?

B WILL YOUR ALARM WORK IN DIFFERENT PLACES OR SCENARIOS?

- Try it in your desk drawer, locker, or under your backpack.
- Put it on the windowsill as a wake-up alarm.
- Use it to prank someone when they turn out the lights.

C MAKE YOUR ALARM MORE EFFECTIVE.

- Snap on a DC motor and sign with a scary monster on it.
- Amplify the sound (try using a paper cup or cone).
- Add lights.

SHARE




PROMOTE YOUR INVENTION! Create a 30-second commercial explaining how useful it is.

HOW DO YOUR CLASSMATES' ALARMS COMPARE WITH THE ORIGINAL DESIGN?

Write a product review for your favorite tech publication.



SHARE YOUR INVENTION ON THE LITTLEBITS APP OR WEBSITE.



CHALLENGE 05

HACK YOUR CLASSROOM

1
HOUR
(MINIMUM)

TIME

○○○○●


LEVEL

USE BITS AND YOUR WITS TO MAKE THE CLASSROOM OF THE FUTURE. You spend a lot of time in your school and classroom. How can you make it even more fun to be there? Pinpoint something that could be easier, especially exciting, or that you wish existed. Use your expertise to design an invention that makes school extra awesome. Perhaps your new invention will become an essential part of the classroom in the future!

CREATE

1

CREATE A LIST OF WAYS YOU COULD MAKE YOUR CLASSROOM BETTER. Need ideas? Ask your friends or teachers about what bothers them or what they'd like improved. You could even level-up something you already like.




2

SELECT THE ISSUE YOU WANT TO WORK ON. Maybe it's something a lot of people feel strongly about, or that you find particularly interesting.

	fun	useful	
A	X	O	
B	O	X	
C	X	X	✓


3

LOOK THROUGH YOUR BITS AND MATERIALS AND THINK ABOUT HOW EACH ONE COULD HELP. Could motion, light, or sound help you achieve your mission? How about buttons or dimmers? If you're not sure what a Bit does or how it could help, snap it into a circuit and start to play with it. If you're still stumped, read through the "Bit Index" section at the beginning of this booklet.




4

SKETCH OUT IDEAS, PICK YOUR FAVORITE, AND CREATE A PROTOTYPE. When you create a physical model of your idea, it is easier to understand how it works. Don't worry about getting everything right on the first try though. The important thing is to just get started and experiment.



PLAY!




TEST YOUR PROTOTYPE. Set up your invention in the classroom and see what you can learn about how it works. Your invention might not work the way you thought, but that's ok, it's part of the invention process! Take note of what works and what doesn't so you can improve it.

REMIX




PRO TIP: EVERY TIME YOU TRY SOMETHING NEW, PLAY WITH YOUR INVENTION TO TEST IT OUT.



DID PLAYING WITH YOUR INVENTION GO THE WAY YOU EXPECTED? Now's your chance to experiment with fixes and improvements. You might need to make things sturdier, work on the mechanics of moving parts, or try using different Bits to achieve your mission.

MAKE WACKY AND WEIRD EXPERIMENTS PART OF YOUR INVENTION PROCESS. Sometimes really great ideas come from unexpected places. Close your eyes and pick a Bit at random. How could this Bit add something cool to your invention? Is it better now or before? Try this with a few different Bits.


SHARE



SHARE YOUR INVENTION ON THE LITTLEBITS APP OR WEBSITE.

CREATE A SHORT COMIC. Show what classroom life was like before and after your invention, and how it has improved things. Inventors often draw comics like these called storyboards to describe how their invention works. These stories are a great way to show people what you did and why it's important.

SET UP AND SHOW OFF YOUR INVENTION TO SOME CLASSMATES OR YOUR TEACHER. How can their feedback help your invention grow? Do they have ideas for improvements? Can they think of other ways it could be used? Their ideas can be great fuel for another round of remixing, playing, and sharing.



CHALLENGE 06

INVENT FOR GOOD

2
HOURS
(MINIMUM)

TIME

●
●
●
●

LEVEL

INVENT A PRODUCT TO MAKE A DIFFERENCE IN SOMEONE ELSE'S LIFE. How does a product get invented? Here at littleBits™ we use the Invention Cycle! When it's time to create a new kit we go through the same process that you do. We brainstorm, create prototypes, play with them, let kids around the country play with them, and we remix over and over again until we get things right. When it's all done, we get to share it with the world. In this challenge you're going to think like a product designer and invent something that helps someone else. Who knows, maybe you'll start the next company like littleBits!

CREATE


1

CREATE A LIST OF IDEAS FOR A PRODUCT. Start by thinking about where there are frustrations or difficulties in someone's life. For example, a person who has trouble hearing might need a way to know if someone is knocking at their door.




2

SELECT THE ISSUE YOU WANT TO WORK ON. It could be the one that sounds the most fun to solve, or creates the biggest difference in someone else's life.



3

LOOK THROUGH YOUR BITS™ AND MATERIALS AND THINK ABOUT HOW EACH ONE COULD HELP. Also take a look at everyday objects you could make better with Bits. For example, if you wanted to design a product that makes doing chores more fun, you could start with a broom.




4


SKETCH OUT IDEAS, PICK YOUR FAVORITE, AND CREATE A PROTOTYPE. Don't worry about getting everything right on the first try. The important thing is to just get started and experiment. Building a physical model of your idea makes it easier to share with others and collect feedback on your design.




PLAY!



REMIX



SHARE




TEST YOUR PROTOTYPE. The first product tester will be you. Pretend you are a customer who just purchased your invention. How well does it do its job? Take notes about what works and what doesn't. You can make changes in the next version.

DID PLAYING WITH YOUR INVENTION GO THE WAY YOU EXPECTED? Now's your chance to experiment with fixes and improvements. Could adding a new Bit™ add important features? Would craft materials make it stronger or give it a new look?

HAVE SOMEONE ELSE TEST YOUR INVENTION AFTER YOU'VE MADE A FEW IMPROVEMENTS. If possible, try to find the type of person you're designing it for. Ask about their favorite parts, and what suggestions they have for making it better. Use their feedback to create an even better version of your invention.

CREATE A SKIT, A PRINT, OR VIDEO ADVERTISEMENT ABOUT WHAT YOU'VE INVENTED. It should explain what your invention is and how it can help make life better for the customer. Share it with the world!

RECRUIT A TEAM. A lot of product designers work in teams because sharing different ideas and perspectives makes for a better design process. Show your invention to some friends. Could you all work together to create an even better product?




CHALLENGE 07

INVENT A CHAIN REACTION CONTRAPTION



TIME




LEVEL

PERFORM A VERY SIMPLE TASK IN A NOT-SO-SIMPLE WAY. Rube Goldberg was a cartoonist who liked to draw really complicated solutions to very simple problems. For example, to turn the page of a book, you might roll a ball down a ramp that hits a box. Then the box falls over and scares a hamster that starts running on its wheel, that winds up a string that turns the page. In this challenge, you're going to design your own multi-step machine. Before you start inventing, there are two important rules:

- 1) Once you start your machine, it needs to be able to run without any help from you. Each step must be triggered automatically by the step before it.
- 2) Your machine should have at least two steps. (Bonus points if you can create more steps!)

CREATE


1 CREATE A LIST OF EVERYDAY ACTIVITIES THAT ONLY TAKE ONE STEP. For example, dropping a can in the recycling bin, flipping on a light switch, or opening a book.




2 SELECT THE EVERYDAY ACTIVITY YOU WANT TO ACCOMPLISH. Which one do you think will be the most fun for this challenge?

- 1 _____
- 2 _____
- 3 _____
- 4 _____
- 5 _____
- 6 _____
- 7 _____
- 8 _____
- 9 _____
- 10 _____


3 LOOK THROUGH YOUR BITS AND MATERIALS AND THINK ABOUT HOW EACH ONE COULD HELP. Could motion, light, or sound help you achieve your mission? How about buttons or dimmers? If you're not sure what a Bit™ does or how it could help, snap it into a circuit and start to play with it. If you're still stumped, read through the "Bit Index" section at the beginning of this booklet.



4 SKETCH OUT IDEAS, PICK YOUR FAVORITE, AND CREATE A PROTOTYPE OF YOUR CONTRAPTION. Don't worry about getting everything right on the first try. The important thing is to just get started and experiment.




PLAY!



TEST YOUR PROTOTYPE. Getting all of these moving pieces to work together is going to be a challenge. Try running your contraption a few times. Record where it works the best and where it isn't so reliable. You can use this information to refine your design.


REMIX



DID PLAYING WITH YOUR INVENTION GO THE WAY YOU EXPECTED? Now's your chance to experiment with fixes and improvements. How can you make your machine more reliable? Maybe you need to strengthen some materials, change the angle of a ramp, or try using different Bits™ for one of your steps.

Set your invention aside and look through your remaining Bits and materials. Could you complete a step with them? Try a few options to see how they compare to what you already have.

SHARE



SHARE YOUR INVENTION ON THE LITTLEBITS APP OR WEBSITE.

TAKE A VIDEO OF YOUR INVENTION AND POST IT TO YOUR FAVORITE SOCIAL MEDIA CHANNEL. People love watching a crazy contraption in action! While you're online, look up some Rube Goldberg cartoons and create your own that describes what your invention is used for and how it works.

Challenge a friend. Show them your invention and see if they can accomplish the same task, but using totally different steps.



CHALLENGE 08

HACK YOUR HABITS

4
HOURS
(MINIMUM)

TIME

•
•
•
•


LEVEL

CREATE AN INVENTION TO TRACK YOUR DAILY HABITS, THEN TRANSFORM YOUR INVENTION TO MAKE LIFE BETTER. How much use does your classroom's recycling bin get? Maybe you could invent something to encourage people to use it more often! How many times a day do you have to go back to your locker because you forgot something? Maybe you could invent something that counts these trips and reminds you to grab what you need! Now's your chance to use your inventing powers to get to the bottom of these types of questions and invent a gadget to make your everyday experience better.

CREATE


1

CREATE A LIST OF THINGS YOU OR YOUR CLASSMATES DO THAT YOU WANT TO KNOW MORE ABOUT. Maybe it's a habit you'd like to improve on (how can I make fewer trips to my locker?), something you're curious about (how many high fives can I get in a day?), or an issue you'd like to help other people understand (why don't your classmates recycle?). Try to list as many different habits as possible.




2

SELECT THE HABIT YOU WANT TO LEARN MORE ABOUT. Is there one that makes you the most happy, passionate, or upset? It's always good to work on something that means a lot to you.



3


LOOK THROUGH YOUR BITS™ AND MATERIALS AND THINK ABOUT HOW EACH ONE COULD MEASURE OR TRACK THAT HABIT. Could the button help you know when something is moved? Could the light sensor detect when something is opened?




PRO TIP: PAIRING AN INPUT BIT™ WITH THE NUMBER (IN COUNT MODE) CAN BE A REALLY HELPFUL COUNTER IN THIS PROJECT.

4

SKETCH OUT IDEAS, PICK YOUR FAVORITE, AND CREATE A PROTOTYPE OF A DATA-COLLECTION MACHINE. Don't worry about getting everything right on the first try. The important thing is to just get started and experiment. Building a physical model of your idea will help you figure out the best way to track habits.




PLAY!



TEST YOUR PROTOTYPE. To get it working reliably, it will probably take a bit of adjusting and redesigning. Once you have it down, you can start tracking your life.

MAKE A HYPOTHESIS ABOUT THE RESULTS YOU WILL GET. For your first trial, decide how long you want to use the invention for. For example, if you're tracking recycling bin use, how many times do you think it gets used daily? Soon you'll have data to test your theory!


REMIX



DID PLAYING WITH YOUR INVENTION GO THE WAY YOU EXPECTED? Now's your chance to experiment with fixes and improvements. Did it gather data well? Do you think it was accurate? Now that you know a little more about your circuit and the habit you're exploring, you can tinker with the invention to make it work better.

HOW CAN YOU ADD NEW FEATURES TO CHANGE PEOPLE'S HABITS? For example, could an invention that tracks use of the recycling bin also reward people for recycling? Would that make them more likely to recycle? Try it out and see if it changes your data.

SHARE



COMPARE THE TRACKING INFORMATION FROM BEFORE AND AFTER YOU MADE CHANGES. Now you know more about how people behave and what motivates them. More importantly, you have the data to prove it! Create a poster that describes the habit you were studying and how your invention affected it. Share it with the world!

HAVE SOMEONE ELSE TRY YOUR INVENTION FOR THE DAY. Do you think your invention could be useful elsewhere? Maybe another classroom wants to encourage recycling, or a friend wants to know what seats in the cafeteria are the most popular.

TROUBLESHOOTING

MY CIRCUIT ISN'T WORKING.

- 1)** Make sure your power Bit™ is on. You should see a red LED illuminated on the board.
- 2)** Try swapping in a new 9 volt battery. Low batteries can cause a circuit to misbehave. Bits™ have different power demands. For example: a DC motor may appear to not be working while a light still shines brightly.
- 3)** Ensure the power cable is securely fastened to both the battery and the power Bit.
- 4)** Make sure your Bits are arranged in the proper order. Remember that you always need a power Bit & power supply at the beginning of each circuit, and an output Bit at the end. If the last Bit in your chain is an input, then it won't do anything to affect your circuit.
- 5)** Check your connections. Are all the Bits securely snapped to each other? You can also try gently wiping down the ends of the bitSnaps with a soft cloth (like your sleeve). Sometimes dust gets in the way of a strong connection. Try unsnapping, cleaning the bitSnaps, and snapping it all back together again.

THE SENSITIVITY OF MY LIGHT SENSOR KEEPS CHANGING.

Are you moving your circuit around between different rooms and spaces? Light conditions can vary quite a bit depending on many different factors like the type of light you're working under, or the time of day (the sun shines through the window at different angles depending on what time it is). If your light sensor is in a new environment (for example, if the sun went down), you might need to adjust the sensitivity again.

I'M HAVING TROUBLE WITH MY TEMPERATURE SENSOR.

1) If the signal coming into the temperature sensor is less than ~50% power, the sensor will be turned off (i.e. it won't pass a temperature signal on to the next Bit.) To turn the temperature sensor on, make sure the Bits before it are sending a strong enough signal. For example, if you have a slide dimmer before the temperature sensor, slide the dimmer all the way up.

2) The power Bit can get warm with a lot of use. If your temperature sensor is near the warm power Bit, it may read a higher temperature than the rest of your surroundings. If this happens, try placing a wire between the power and temperature sensor to give them some space.

MY SERVO IS SHAKING.

- 1)** Check your battery. Try swapping in a new one. Low batteries can cause the servo to misbehave.
- 2)** Make sure the servo's wire is firmly connected to the board.
- 3)** The servo motor can only take so much weight. If you have something attached to it, you might need to lighten the load.
- 4)** If your servo is receiving a signal from a light sensor Bit, the light conditions may have had an effect on your servo. For example, some fluorescent and LED light fixtures flicker at a very high frequency and cause the light sensor to send jittery signals. If you suspect this problem, try moving to a different light environment.

HOW CAN I CHANGE THE POSITION OF MY MECHANICAL ARM?

Did you know that you can remove the servo hub from the servo motor? To do this, hold the black part of the servo motor and pull the hub away from it. It should pop off. Then you can rotate the position of the arm to your liking and press the hub back on. You may need to try this a few times to get it just right. Be careful to align the little teeth on the servo gear with the ridges inside the hole on the servo hub.

I'M HAVING TROUBLE ATTACHING THE WHEEL/MOTORMATE TO MY DC MOTOR.

The shaft of the DC motor and the holes in the wheel and motorMate are all shaped like a "D". Make sure that the flat edge of the shaft on the DC motor aligns with the flat edge of the hole in the wheel/motorMate.

STILL HAVING TROUBLE?

Visit littleBits.cc/faq or contact our customer service team at support@littleBits.cc.

CONTINUE YOUR INVENTOR JOURNEY

The inventing doesn't stop here! Discover new friends, new challenges, and new invention adventures online and on the littleBits™ Invent App.

EXPLORE LITTLEBITS.CC AND THE LITTLEBITS INVENT APP FOR...

MORE INVENTIONS!


See what other Inventors have made with littleBits.

MORE CHALLENGES!

Take on new challenges and submit your solutions.

MORE BITS!

Add Bits and Kits to your collection for bigger and better inventions!



COMMUNITY

Find a local littleBits Chapter or share your questions and ideas on our forum.

▲ WARNING

- This product contains small magnets. Swallowed magnets can stick together across intestines causing serious infections and death. Seek immediate medical attention if magnets are swallowed or inhaled.
- Most Bits are small parts. DO NOT allow children under 3 years old to play with or near this product.
- NEVER connect any modules or circuits to any AC electrical outlet.
- Do not touch or hold any moving parts of modules while they are operating.
- Keep conductive materials (such as aluminum foil, staples, paper clips, etc.) away from the circuit and the connector terminals.
- Always turn off circuits when not in use or when left unattended.
- Never use Bits in or near any liquid.
- Never use in any extreme environments such as extreme hot or

cold, high humidity, dust or sand.

- Bits are subject to damage by static electricity. Handle with care.
- Some modules may become warm to the touch when used in certain circuit designs. This is normal. Rearrange modules or discontinue using if they become excessively hot.
- Discontinue use of any Bits that malfunction, become damaged or broken.

VERY IMPORTANT NOTE

- Several projects in this kit involve the use of sharp objects. These tools should be used ONLY under direct adult supervision.

BATTERIES

- non-rechargeable batteries are not to be recharged
- rechargeable batteries are to be removed from the product before being charged
- rechargeable batteries are only to be charged under adult supervision

INSTRUCTIONS

We recommend using littleBits brand 9-volt batteries, but standard alkaline or standard rechargeable batteries may also be used. Properly discard and replace exhausted batteries.

- Do not connect the two battery terminals to any conducting material.

CARE AND CLEANING

Clean Bits ONLY by wiping with a dry cloth. If necessary, isopropyl alcohol on a cloth may be used sparingly, and then wipe with a dry cloth.

DO NOT use any other cleaning products on modules.

FC RADIO AND TELEVISION INTERFERENCE

FCC ID: SH6MDBT40
This device complies with the limits for a Class B digital device,

pursuant to Part 15 of the FCC rules. Operation is subject to the following two conditions:

- 1) This device may not cause harmful interference, and
- 2) this device must accept any interference received, including interference that may cause undesired operation.

These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on,

the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and the receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Changes and modifications not expressly approved by the manufacturer or registrant of this equipment can void your authority to operate this equipment under Federal Communications Commissions rules.

GOT A QUESTION?

Visit littlebits.cc/faq for troubleshooting and additional support.

littleBits Electronics Inc.
601 W 26th Street, M274
NY, NY 10001
(917)464-4577

www.littlebits.cc

★ Released under CERN Open Hardware License, Version 1.2
Designed By: littleBits Electronics, Inc.

© 2016 littleBits Electronics, Inc.
All rights reserved.
Made in China

littleBits, Bit, Bits, Circuits in Seconds, and Make Something That Does Something are trademarks of littleBits Electronics, Inc.

All other marks are the property of their respective owners.



p1
POWER



p3
USB POWER



o3
RGB LED




o6
BUZZER



i3
BUTTON



i12
**TEMPERATURE
SENSOR**



o2
LONG LED



i13
LIGHT SENSOR



i16
PULSE




o21
NUMBER




i5
SLIDE DIMMER




w10
INVERTER




w7
FORK




w1
WIRE



o13
FAN



o25
**DC
MOTOR**



o11
**SERVO
& HUB**

littleBits **STEAM STUDENT SET**

ACCESSORIES

- 9V battery & cable
- USB power adapter & cable
- hook & loop strips (x2)
- mechanical arms (x3)
- motorMates (x4)
- mounting boards (x2)
- screws (x4)
- screwdrivers (x2)
- servo hub
- servo mount
- shoes, magnet (x12)
- shoes, hook & loop (x12)
- wheels (x2)